

- 5GC OMC Http External Restful Interfaces
  - 1 状态管理
  - 2 故障管理
    - 2.1 告警上报
    - 2.2 获取网元告警
  - 3 配置管理
    - 3.1 参数配置表
    - 3.2 获取参数
    - 3.3 配置参数
    - 3.4 创建网元
  - 4 性能管理
    - 4.1 任务管理
    - 4.2 订阅任务数据上报
    - 4.3 黄金指标上报
    - 4.4 测量数据主动上报
    - 4.5 测量数据获取/补采
  - 5 跟踪管理
    - 5.1 订阅管理
  - 6 操作维护
    - 6.1 MML命令
      - 6.1.1 MML命令格式
    - 6.2 MML接口
  - 7 北向资源配置数据接口
    - 7.1 查询资源数据接口

# 5GC OMC Http External Restful Interfaces

---

## 1 状态管理

---

- URI:

```
/api/rest/systemManagement/v1/elementType/{elementTypeValue}/objectType/systemState
```

说明:

```
** elementTypeValue=smf/amf/..查询的网元网元类型
```

• Method:

GET

• Return:

```
"data": [
  {
    "AMF_0": {
      "error": {
        "errorCode": "1",
        "errorInfo": "Internal server error, NF connect refused"
      },
      "ipAddress": "192.168.2.188"
    }
  },
  {
    "SMF_0": {
      "ipAddress": "192.168.1.232",
      "systemState": {
        "capability": 10000,
        "cpuUsage": {
          "nfCpuUsage": 2,
          "sysCpuUsage": 52
        },
        "diskSpace": {
          "partitionInfo": [
            {
              "total": 1920,
              "used": 0
            },
            {
              "total": 393,
              "used": 13
            },
            {
              "total": 48700,
              "used": 32431
            },
            {
              "total": 1965,
              "used": 0
            },
            {
              "total": 5,
              "used": 0
            }
          ]
        }
      }
    }
  }
]
```

```
},
{
  "total": 1965,
  "used": 0
},
{
  "total": 55,
  "used": 55
},
{
  "total": 63,
  "used": 63
},
{
  "total": 91,
  "used": 91
},
{
  "total": 49,
  "used": 49
},
{
  "total": 55,
  "used": 55
},
{
  "total": 73,
  "used": 73
},
{
  "total": 91,
  "used": 91
},
{
  "total": 1475,
  "used": 206
},
{
  "total": 49,
  "used": 49
},
{
  "total": 393,
  "used": 13
},
{
  "total": 393,
  "used": 0
},
{
  "total": 73,
  "used": 73
},
{
  "total": 63,
  "used": 63
}
```

```
    ],
    "partitionNum": 19
  },
  "expiryDate": "2025-02-28",
  "memUsage": {
    "nfUsedMem": 163992,
    "sysMemUsage": 1345,
    "totalMem": 4025608
  },
  "serialNum": "13740126",
  "version": "1.5.3.2"
}
}
},
{
  "SMF_1": {
    "ipAddress": "192.168.1.173",
    "systemState": {
      "capability": 10000,
      "cpuUsage": {
        "nfCpuUsage": 0,
        "sysCpuUsage": 69
      },
      "diskSpace": {
        "partitionInfo": [
          {
            "total": 3966,
            "used": 0
          },
          {
            "total": 797,
            "used": 0
          },
          {
            "total": 200559,
            "used": 5968
          },
          {
            "total": 3987,
            "used": 0
          },
          {
            "total": 5,
            "used": 0
          },
          {
            "total": 3987,
            "used": 0
          },
          {
            "total": 797,
            "used": 0
          }
        ],
        "partitionNum": 7
      },
      "expiryDate": "2024-12-31",
```

```
    "memUsage": {
      "nfUsedMem": 212136,
      "sysMemUsage": 720,
      "totalMem": 8167360
    },
    "serialNum": "13740272",
    "version": "1.5.3.3"
  }
}
]
```

## 2 故障管理

### 2.1 告警上报

- URI

```
/api/rest/faultManagement/v1/elementType/{elementTypeValue}/objectType/alarms
```

- Method

POST

- Relation

NF->OMC

- Body

```
type Alarm struct {
  AlarmSeq      int    `json:"alarmSeq"`
  AlarmId       string `json:"alarmId"`
  NeId          string `json:"neId"`
  AlarmCode     int    `json:"alarmCode"`
  AlarmTitle    string `json:"alarmTitle"`
  EventTime     string `json:"eventTime"`
  AlarmType     string `json:"alarmType"`
  OrigSeverity  string `json:"origSeverity"`
  PVFlag        string `json:"pvFlag"`
  NeName        string `json:"neName"`
  NeType        string `json:"neType"`
  ObjectName    string `json:"objectName"`
}
```

```

LocationInfo    string `json:"locationInfo"`
Province        string `json:"province"`
AlarmStatus     int    `json:"alarmStatus"`
SpecificProblem string `json:"specificProblem"`
SpecificProblemID string `json:"specificProblemID"`
AddInfo         string `json:"addInfo"`
}

```

## 2.2 获取网元告警

- URI

```
/api/rest/faultManagement/v1/elementType/{elementTypeValue}/objectType/alarms
```

- Method

GET

- Relation

OMC->NF

- Body

n/a

- Return

```

type Alarms struct {
    Alarms []struct {
        AlarmSeq      int    `json:"alarmSeq"`
        AlarmId       string `json:"alarmId"`
        NeId          string `json:"neId"`
        AlarmCode     int    `json:"alarmCode"`
        AlarmTitle    string `json:"alarmTitle"`
        EventTime     string `json:"eventTime"`
        AlarmType     string `json:"alarmType"`
        OrigSeverity string `json:"origSeverity"`
        PVFlag       string `json:"pvFlag"`
        NeName       string `json:"neName"`
        NeType       string `json:"neType"`
        ObjectName   string `json:"objectName"`
        LocationInfo string `json:"locationInfo"`
        Province     string `json:"province"`
        AlarmStatus  int    `json:"alarmStatus"`
        SpecificProblem string `json:"specificProblem"`
    }
}

```

```
        SpecificProblemID string `json:"specificProblemID"`
        AddInfo            string `json:"addInfo"`
    } `json:"Alarms"`
}
```

## 3 配置管理

### 3.1 参数配置表

- 类型定义 (type)

- string

**filter**指定字符串长度，如：`"filter": "6~100"`，字符串的长度范围，如果单个数字表示最大长度

- ipv4

**filter**忽略

- ipv6

**filter**忽略

- int

**filter**指定整型数的范围，如：`"filter": "100~999"`

- enum

`"filter": '{"0": "http", "1": "https"}'`

- bool

`"filter": '{"0": "false", "1": "true"}'`

- regex

**filter**为正则表达式

- 可选 (optional)

- **true**, 默认值, 表示该字段为可选填, 没有写该属性项时optional为true (兼容以前配置文件)
- **false**, 表示必填项

## • Example

```
UDM:
system:
  display: "System"
  list:
    - name: "serviceIP"
      type: "ipv4"
      value: "172.16.5.140"
      optional: "false"
      access: "read-write"
      filter: ''
      display: "Service IP"
      comment: ""
    - name: "servicePort"
      type: "int"
      value: "8080"
      access: "read-write"
      filter: "0~65535"
      display: "Service Port"
      comment: "0~65535"
subsSmfSelection:
  display: "Subs Smf Selection"
  array:
    - name: "index"
      type: "int"
      value: "0"
      access: "read-write"
      filter: '0~15'
      display: "Index"
      comment: "0~15"
    - name: "name"
      type: "string"
      value: 'def_ambr'
      access: "read-write"
      filter: '^.{1,32}$'
      display: "Name"
      comment: "0~32"
    - name: "snssai"
      type: "string"
      value: '1-000001'
      access: "read-write"
      filter: '^\\d{1,3}[A-Fa-f0-9]{6}$'
      display: "Snssai"
      comment: ""
    - name: "dnnList"
      type: "int"
      value: '0'
      access: "read-write"
      filter: '0~3'
```



```
display: "Dnn List"
comment: ""
array:
  - name: "index"
    type: "int"
    value: "0"
    access: "read-write"
    filter: '0~15'
    display: "index"
    comment: "0~15"
  - name: "dnn"
    type: "string"
    value: 'cmnet'
    access: "read-write"
    filter: '^.{1,32}$'
    display: "Dnn"
    comment: "0~32"
  - name: "defaultDnnInd"
    type: "bool"
    value: 'true'
    access: "read-write"
    filter: 'false;true;'
    display: "default Dnn Indicator"
    comment: ""
```

完整文件具体请参考 `udm_param_config.yaml`

## 3.2 获取参数

- URI

```
/api/rest/systemManagement/v1/elementType/{elementTypeValue}/objectType/config/{paraName}?loc={index0}/{paraName1}/{index1}/...
```

### 说明

```
elementTypeValue: udm, smf, amf... 网元类型
udm paraName: system, subsUEAmbr, subsSmfSelection ...
非Array的参数, 忽略loc
```

- Params

- loc 多层表的定位信息

- Method

- Return

```
/api/rest/systemManagement/v1/elementType/udm/objectType/config/system
```

```
{
  "data": [
    {
      "serviceIP": "172.16.5.140",
      "servicePort": "8080",
      "...": "..."
    }
  ]
}
```

```
/api/rest/systemManagement/v1/elementType/udm/objectType/config/subsSmfSelection?loc=1/dnnList
```

```
{
  "data": [
    {
      "index": "0",
      "dnn": "cmnet",
      "...": "..."
    },
    {
      "index": "1",
      "dnn": "ims",
      "...": "..."
    }
  ]
}
```

### 3.3 配置参数

- URI

```
/api/rest/systemManagement/v1/elementType/{elementTypeValue}/objectType/config/{paraName}?loc={index0}/{paraName1}/{index1}
```

- Params
  - loc 多层表的定位信息
- Method

POST/PUT/DELETE

说明:

单层表不支持POST/DELETE操作

- Body

```
{  
  "serviceIP": "172.16.5.140",  
  "servicePort": "8080",  
  "...": "..."  
}
```

说明:

DELETE操作不带Body

## 3.4 创建网元

- URI

/api/rest/systemManagement/v1/elementType/{elementTypeValue}/objectType/neInfo

- Params

N/A

- Method

POST

- Body

```
{  
}
```

## 4 性能管理

---

### 4.1 任务管理

- URI

```
/api/rest/performanceManagement/v1/elementType/{elementTypeValue}/objectType/measurementTask?id={taskId1}&id={taskId2}
```

- Method

POST/PUT/DELETE/PATCH

- Params

taskId=1&taskId=2

- POST: 增加测量任务，激活任务，不带id参数，id在body
- PUT: 修改测量任务，激活任务，不带id参数，id在body
- DELETE: 删除测量任务，不需要带body，带id参数，可带多个
- PATCH: 暂停测量任务，不需要带body，带id参数，可带多个

测量任务创建/修改后暂时存储在OMC数据库，激活任务时再下发到网元

- Relation NF

OMC -> NF/NF -> OMC

- Body

下发测量任务的报文结构

```

type MeasureTask struct {
    Tasks []struct {
        Id int `json:"Id"`

        StartTime string `json:"StartTime"`
        EndTime string `json:"EndTime"`

        Schedule struct {
            Type string `json:"Type"` // 计划类型: Weekly/Monthly, 如果type
            为"", 则任务以StartTime和EndTime为条件进行统计, 否则以Shedule方式进行
            Days []int `json:"Days"` // Weekly: [0,1,...5,6], 0~6表示星期日
            ~星期六, Monthly: [1,2,3,...,30,31]一个月的几天
            Periods []struct {
                Start string `json:"Start"` // 零点或者零点加测量粒度的整数倍
                00:15:00
                End string `json:"End"` // 零点加测量粒度的整数倍 08:45:00,
                16:15:00
            } `json:"Periods"`
        } `json:"Schedule"`

        GranuloOption string `json:"GranuloOption"` // 测量粒度选项:
        15M/30M/60M/24H

        KPISet []struct {
            Code string `json:"Code"` // 统计编码 如: SMFHA01
            KPIS []string `json:"KPIS"` // 指标项集合
            ["SMF.AttCreatePduSession", "SMF.AttCreatePduSession._Dnn"]
        } `json:"KPISet"`
    } `json:"Tasks"`

    NotifyUrl string `json:"NotifyUrl"` /* 数据上报URL
    "http://x.x.x.x:xxxx/api/rest/performanceManagement/v1/elementType/smf/objectT
    ype/measureReport" */
}

```

- Return

## 4.2 订阅任务数据上报

- URI

```

/api/rest/performanceManagement/v1/elementType/{elementTypeValue}/objectType/m
easureReport

```

- Method

POST

- Relation

NF -> OMC

- Body

网元返回测量数据的报文结构

```
type MeasureReport struct {
    Id          int    `json:"Id"`
    Timestamp   string `json:"TimeStamP"`
    NeName      string `json:"NeName"`
    RmUID       string `json:"rmUID"`
    NeType      string `json:"NeType"`

    Report struct {
        Period struct {
            StartTime string `json:"StartTime"`
            EndTime   string `json:"EndTime"`
        } `json:"Period"`

        Datas []struct {
            Code string `json:"Code"` // 统计编码 如: SMFHA01
            KPIs []struct {
                KPIID string `json:"KPIID"` // 指标项, 如:
                SMF.AttCreatePduSession._Dnn
                KPIValues []struct {
                    Name string `json:"Name"` // 单个的写"Total", 或者指标项有
                    多个测量项, 如Dnn的名称写对应的Dnn"cmnet"/"ims"
                    Value int64  `json:"Value"`
                } `json:"KPIValues"`
            } `json:"KPIs"`
        } `json:"Datas"`
    } `json:"Report"`
}
```

## 4.3 黄金指标上报

- URI

```
/api/rest/performanceManagement/v1/elementType/{elementTypeValue}/objectType/kpiReport/{index}
```

index取值范围: 0-1439

- Method

POST

- Body

```
type KpiReport struct {
    Timestamp string `json:"TimeStamp"`
    Task      struct {
        Period struct {
            StartTime string `json:"StartTime"`
            EndTime   string `json:"EndTime"`
        } `json:"Period"`
        NE struct {
            NEName string `json:"NEName"`
            RmUID  string `json:"rmUID"`
            NeType string `json:"NeType"`
            KPIs  []struct {
                KPIID string `json:"KPIID"`
                Value int    `json:"Value"`
                Err  string `json:"Err"`
            } `json:"KPIs"`
        } `json:"NE"`
    } `json:"Task"`
}
```

## 4.4 测量数据主动上报

- URI

```
/api/rest/performanceManagement/v1/elementType/{elementTypeValue}/objectType/measurement/{index}
```

- Method

POST

- Relations

NF -> OMC

- Params

NA

- Body

## 网元主动上报测量数据的报文结构

```
type Measurement struct {
    Index      int    `json:"Index"` // 1天当中测量时间粒度(如15分钟)的切片索引: 0~95
    Timestamp  string `json:"TimeStamp"`
    NeName     string `json:"NeName"` // UserLabel
    RmUID      string `json:"rmUID"`
    NeType     string `json:"NeType"` // 网元类型
    PmVersion  string `json:"PmVersion"` // 性能数据版本号
    Dn         string `json:"Dn"` // (???)网元标识, 如:RJN-CMZJ-TZ,SubNetwork=5GC88,ManagedElement=SMF53456,SmfFunction=53456
    Period     string `json:"Period"` // 测量时间粒度选项: 5/15/30/60
    TimeZone  string `json:"TimeZone"` // 时区, 如: "UTC+8"
    StartTime  string `json:"StartTime"`

    Datas []struct {
        ObjectType string `json:"ObjectType"` // 网络资源类别名称, Pm指标项列表中为空间粒度 如: SmfFunction
        KPIs []struct {
            KPIID      string `json:"KPIID"` // 指标项, 如: SMF.AttCreatePduSession._Dnn
            KPIValues []struct {
                Name string `json:"Name"` // 单个的写"Total", 或者指标项有多个测量项, 如Dnn的名称写对应的Dnn"cmnet"/"ims"
                Value int64  `json:"Value"`
            } `json:"KPIValues"`
        } `json:"KPIs"`
    } `json:"Datas"`
}
```

- Return

Code: 204, no content

## 4.5 测量数据获取/补采

- URI

```
/api/rest/performanceManagement/v1/elementType/{elementTypeValue}/objectType/measurement/{index}
```

- Method

GET



- Relations

OMC -> NF

- Params

NA

- Body

NA

- Return

网元返回测量数据的报文结构

```
type Measurement struct {
    Index      int    `json:"Index"`           // 1天中测量时间粒度(如15分钟)的切片索引: 0~95
    Timestamp  string `json:"TimeStamp"`
    NeName     string `json:"NeName"`       // UserLabel
    RmUID      string `json:"rmUID"`
    NeType     string `json:"NeType"`       // 网元类型
    PmVersion  string `json:"PmVersion"`    // 性能数据版本号
    Dn         string `json:"Dn"`           // (???)网元标识, 如:RJN-CMZJ-TZ,SubNetwork=5GC88,ManagedElement=SMF53456,SmfFunction=53456
    Period     string `json:"Period"`       // 测量时间粒度选项: 5/15/30/60
    TimeZone   string `json:"TimeZone"`
    StartTime  string `json:"StartTime"`

    Datas []struct {
        ObjectType string `json:"ObjectType"` // 网络资源类别名称, Pm指标项列表中为空间粒度 如: SmfFunction
        KPIs []struct {
            KPIID      string `json:"KPIID"` // 指标项, 如: SMF.AttCreatePduSession._Dnn
            KPIValues []struct {
                Name string `json:"Name"` // 单个的写"Total", 或者指标项有多个测量项, 如Dnn的名称写对应的Dnn"cmnet"/"ims"
                Value int64  `json:"Value"`
            } `json:"KPIValues"`
        } `json:"KPIs"`
    } `json:"Datas"`
}
```

## 5 跟踪管理

# 5.1 订阅管理

- 创建订阅

- URI

```
/api/rest/traceManagement/v1/subscriptions
```

- Method

POST

- Relations

OMC front-end->OMC back-end, OMC -> NF

- Body

```
type TraceTask struct {  
    TraceType string `json:"traceType"`  
    StartTime string `json:"startTime"`  
    EndTime   string `json:"endTime"`  
    Imsi      string `json:"imsi"`  
    Msisdn    string `json:"msisdn"`  
    SrcIp     string `json:"srcIp"`  
    DstIp     string `json:"dstIp"`  
    SignalPort int16 `json:"signalPort"`  
    NeType    string `json:"neType"`  
    NeId      string `json:"neId"`  
    UeIp      string `json:"ueIp"`  
    Interfaces []string `json:"interfaces"`  
}
```

Example:

```
{  
    "traceType": "Interface",  
    "startTime": "2023-07-04 13:00:00",  
    "endTime": "2023-07-04 19:00:00",  
    "neType": "UDM",  
    "neId": "SZ_01",  
    "interfaces": ["N8", "N10"]  
}
```

- Return

Code=204 non-content

- 修改订阅

- URI

```
/api/rest/traceManagement/v1/subscriptions
```

- Method

PUT

- Relations

OMC front-end->OMC back-end, OMC -> NF

- Body

```
type TraceTask struct {
    Id          int      `json:"id"`
    TraceType   string   `json:"traceType"`
    StartTime   string   `json:"startTime"`
    EndTime     string   `json:"endTime"`
    Imsi        string   `json:"imsi"`
    Msisdn      string   `json:"msisdn"`
    SrcIp       string   `json:"srcIp"`
    DstIp       string   `json:"dstIp"`
    SignalPort  int16    `json:"signalPort"`
    NeType      string   `json:"neType"`
    NeId        string   `json:"neId"`
    UeIp        string   `json:"ueIp"`
    Interfaces  []string `json:"interfaces"`
}
```

Example:

```
{
  "id": 1,
  "traceType": "Interface",
  "startTime": "2023-07-04 13:00:00",
  "endTime": "2023-07-04 19:00:00",
  "neType": "UDM",
  "neId": "SZ_01",
```

```
"interfaces": ["N8", "N10", "N11"]
}
```

- Return

Code=204 non-content

- 删除订阅

- URI

```
/api/rest/traceManagement/v1/subscriptions?id={id1}&id={id2}
```

- Method

DELETE

- Relations

OMC front-end->OMC back-end, OMC -> NF

- Params

id: 订阅任务id, 支持多个

- Body

NA

- Return

Code=204, non-content

- 查询订阅 (暂不实现, 直接从数据库查询)

- URI 查询单个订阅:

```
/api/rest/traceManagement/v1/subscriptions?id={id}
```

查询所有订阅:

```
/api/rest/traceManagement/v1/subscriptions
```

- Method

GET

- Body

NA

- Return

```
{
  "data": [
    {
      "id": 1,
      "traceType": "Interface",
      "startTime": "2023-07-04 13:00:00",
      "endTime": "2023-07-04 19:00:00",
      "neType": "UDM",
      "neId": "SZ_01",
      "interfaces": ["N8", "N10", "N11"]
    }
  ]
}
```

## 6 操作维护

### 6.1 MML命令

#### 6.1.1 MML命令格式

- 命令格式

```
oper object:parameter1={value1},parameter2={value2},parameter3={value3};
```

- 操作(operation)

- 根据实际操作可选用如下动作，如果没有合适的可自行增加，要做到简洁直观

```
add: 增加
mod(set): 修改/设置
del(rmv): 删除
dsp(lst): 查询显示
bak: 备份
exp: 导出
imp: 导入
bat: 批量
exec(run): 执行
act/dea: 激活/去激活
```

- 与对象之间采用空格分隔

- 对象(object)

- 操作的对象，如签约数据(sub/udmuser)/鉴权数据(auth/authdat), n7接口(n7server)
- 对象名称用所操作对象的英文名(或缩写), 为字母或者数字的组合, 不含空格, "-", "\_"等特殊字符
- 使用":"与参数进行分隔

- 参数(param)

- 参数名采用英文常用名/约定俗成的缩写/缩略语等, 如imsi, msisdn, ip, port等, 为字母或者数字的组合, 不含空格, "-", "\_"等特殊字符
- 参数值为字符串, 如有":", ",", ";", "\"字符, 需加\"进行转义
- 参数之间用","进行分隔

- 命令结束符";", 操作/对象/参数均采用小写字母 (HW采用的都是大写字母)

- 目前现有的各个网元的命令格式

除了UDM签约数据/鉴权数据的MML格式和上述格式基本一致, 各个网元的系统参数MML都不一样, 需统一成上述格式

- UDM鉴权数据/签约数据

```
add
authdat:imsi=460000100000030,ki=805DADC6E8A54A0D59D622C7A04D08E0,amf=800
0,algo=0,opc=CF7FD414E05754CFE08B4FE7F2EF2A36
```

- UDM系统参数

```
set n8ip 172.16.5.130
```

- AMF系统参数

```
set n8_ip 192.168.1.121
```

- SMF/UPF系统参数

```
set n7 server <http|https> <ip> <port>
```

## 6.2 MML接口

- URI

```
/api/rest/operationManagement/v1/elementType/{elementTypeValue}/objectType/mml  
?ne_id={neId}
```

- Related NF

OMC front-end -> OMC back-end

OSS -> OMC (北向接口)

- Params

ne\_id={neId}

- Method

POST

- Body

```
{  
  "mml": [  

```

```
    "date",
    "list ver",
    "list lic",
    "list comm"
  ]
}
```

- Return

```
{
  "data": [
    "2023-05-11 17:52:32.37333745 +0800 CST m=+28762.188435351\n",
    "16.1.1\n",
    "Expiry date: 2024-12-31, sn: 13740272\n",
    "COMMAND NOT FOUND, opr: list, obj: comm\n"
  ]
}
```

## 7 北向资源配置数据接口

### 7.1 查询资源数据接口

- URI

```
/api/rest/resourceManagement/{apiVersion}/elementType/{elementTypeValue}/objectType/{objectTypeValue}?rmUIDs={rmUIDValues}&fields={attributeNames}
```

- Related NF

OMC -> NF

OSS -> OMC (北向接口)

- Params

- rmUIDs={rmUIDValues}

可携带多额rmUID(统一资源定位符), OMC->NF不带

- fields={attributeNames}



属性域集合={属性名列表}, 指定资源对象多个属性名的英文逗号分割, 一个属性名时无英文逗号。

- Method

GET

- Body

```
GET /api/rest/resourceManagement/v1/elementType/SMF/objectType/ManagedElement?
rmUIDs=1101AGTHXSMF0000015704000100&fields=UserLabel HTTP/1.1
accessToken: 52661fbd-6b84-4fc2-aa1e-17879a5c6c9b
Host: serverIP:port
Content-Type: application/json; charset=UTF-8
Content-Length:...
{
}
```

- Return

```
HTTP/1.1 200 OK
Content - Type: application/json
Content-Length:...
{
  "data": [{
    "rmUID": "1101AGTHXSMF0000015704000100",
    "UserLabel": "SMFRJBJJC01",
    ...
  }]
}
```